

FIELD ANALYZER



▶ Description

- ISOLATION CHECK
- POWER(FA, TOTAL) MEASUREMENT
- PORTABLE
- SMALL SIZE AND WEIGHT
- BEST PRICE VERSUS PERFORMANCE
- LOW POWER CONSUMPTION
- SUITABLE FOR REPEATER INSTALLATION
- BATTERY OPERATION

▶ Function

- INPUT POWER MEASUREMENT
- ISOLATION MEASUREMENT
- FA POWER MEASUREMENT
- OVERPOWER ALARM

▶ Specifications

| | Parameters | AFA-176020TX | 비 고 |
|-------------|-----------------|----------------|-------------------------------------|
| Transmitter | Frequency Range | 1750 ~ 1770MHz | CW, Selected Frequency |
| | Output Level | +30dBm | |
| | Output Port | 1 Ports | |
| | Supply Voltage | +9V | DC Adapter Cigar Jack Battery |
| | Size[mm] | 195 x 87 x 55 | |

Actipass Co., Ltd.

451, Hagal-Dong, Giheung-Gu, Yongin-Si, Kyunggi-Do, Korea

TEL : 82-31-201-7589 FAX : 82-31-204-7502

E-Mail : steve@actipass.com / actipass@actipass.com www.actipass.com

| | | | |
|--|------------------|---------------|--|
| | Operating Temp. | 0 ~ 50℃ | |
| | Current | 0.8A(max.) | |
| | In/Out Connector | N type(F) | |
| | Battery | Continuous 3H | |

* The specification can be modified upon buyer's requests.

* All specifications are subject to change without notice.

* The latest specifications are available at www.actipass.com
Receiver

| | Item | AFA-176020TX | 비 고 |
|--------------------|-----------------------------|-----------------|--|
| Transmitter | Frequency Range | 1750 ~ 1770MHz | BW : 20MHz |
| | Input Port | 1 Ports | |
| | Input Level Range | -40 ~ -90dBm | ± 1.0dB |
| | RBW | 30KHz | |
| | Power Accuracy | ± 1dB @ (0~50℃) | |
| | Isolation Measurement | 70 ~ 120dB | ± 1.0dB |
| | Input Power Measurement | -40 ~ -90dBm | ± 1.0dB |
| | Power Measurement per FA | -40 ~ -90dBm | ± 1.0dB |
| | Supply Voltage | +9V | DC Adapter Cigar Jack Battery 사용 |
| | Size[mm] | 195 x 87 x 55 | |
| | Operating Temp. | 0 ~ 50℃ | |
| | Current | 0.5A(max.) | |
| | In/Out Connector | N type (F) | |
| | Battery | Continuous 10H | |